

More binary homework: ALIENS!**Due Monday, April 3****Background assumptions** We imagine an alien language which has only three words:

- 40% of the words are 1111111. Abbreviate this word with **A**. It is seven bits long.
- 30% of the words are 00000. Abbreviate this word with **B**. It is five bits long.
- 30% of the words are 10101010. Abbreviate this word with **C**. It is eight bits long.

1. Decipher the following messages. That is, describe the sequence of alien words which produced them. For example, if you believe the message is $\overbrace{00000}^B \overbrace{1111111}^A \overbrace{10101010}^C \overbrace{10101010}^C$ you would report that the aliens were signalling **BACC**.

a) The aliens have xored a message with a pseudorandom bit string with about 5% 1's.

```
10111 11111 11111 01010 10111 11110 01001 01010 10000 00101 01010 11111 11101
01110 00000 10111 11101 01010 11101 11000 00
```

b) The aliens have xored a message with a pseudorandom bit string with about 10% 1's.

```
10101 00001 10011 01111 00000 11111 11000 10110 10111 01010 10111 11111 11011
10000 11000 11010 10100 00001 11111 11111 010
```

2. The aliens now xor two messages and send the resulting bitstream.

```
11111 11111 00000 10111 11101 01011 01001 01000 00101 00101 00000 01010 00010
10101 11100 11111 11110 10101 00000 00111 11
```

Reconstruct both messages as well as you can from this information.

3. The aliens created a pseudorandom bitstream with 50% 1's and 50% 0's, **but** they made a major error. They used the same stream to conceal three different messages. The concealed messages are displayed below. Decipher as much as you can of all three messages.

First message

```
00100 11011 10110 10110 10101 11110 11101 11111 11110 00000 10010 01110 10110
00011 01111 01011 00000 10110 11000 10010 00101 1
```

Second message

```
00100 11001 00011 01001 11010 01110 11100 10101 01110 00011 01111 01110 11100
10110 00000 10100 11111 00110 11011 01111 01111 0
```

Third message

```
01110 01110 11100 00110 11010 01110 00011 11111 11011 01010 00111 01110 00011
00110 00101 11110 01010 01100 01110 00101 110
```

Hint**Xor of first and second messages**

```
00000 00010 10101 11111 01111 10000 00001 01010 10000 00011 11101 00000 01010 10101 01111 11111
11111 10000 00011 11101 01010 1
```

Xor of first and third messages

```
01010 10101 01010 10000 01111 10000 11110 00000 00101 01010 10101 00000 10101 00101 01010 10101
01010 11010 10110 10111 111
```

Xor of second and third messages

```
01010 10111 11111 01111 00000 00000 11111 01010 10101 01001 01000 00000 11111 10000 00101 01010
10101 01010 10101 01010 101
```